








This quick start guide is a quick reference for users to install and operate the dome camera and only provides basic information on the camera's settings and operation. Before attempting to connect, configure and operate the dome camera, please read the user manual thoroughly.

Box Contents

		
IP Dome Camera	Self-Tapping Screws	Plastic Anchors
		
Rubber Washers (outdoor camera only)	Security Torx Tool	Quick Start Guide
		
	CD	

Connecting to the IP Camera

To access the camera setup menu, you need to install the viewer software on your PC or recorder. The viewer software will install automatically the first time you connect to the camera. If your internet browser doesn't install the viewer software, check the security settings or ActiveX controls and plug-in settings. If your internet browser asks for permission to install the ActiveX control, you must allow the ActiveX control to continue the installation.

To enable installation of ActiveX controls on Internet Explorer:

1. From the **Tools** menu, click **Internet Options**.
2. Click the **Security** tab and then click the **Internet** icon.
3. Click **Custom Level** and ensure that all **ActiveX controls and plug-ins** are set to **Enable** or **Prompt**.

To add the camera to your trusted sites:

1. From the **Tools** menu, click **Internet Options**.
2. Click the **Security** tab and then click the **Trusted Sites** icon.
3. Click **Sites**.
4. Type the **IP Address** of the camera. Ensure that the **Require server verification** check box is cleared.

For additional information on adjusting the settings of your internet browser contact technical support at 1-877-855-1349

Default Username and Password

The username and password are case sensitive. It is strongly recommended that the password be changed after the initial setup to prevent unauthorized access.

Username – Admin

Password – 1234

Power


The Indoor IP Dome Cameras use Power over Ethernet (PoE). When using PoE, make sure the Power Sourcing Equipment (PSE) is in use in the network.

Power Source	Operational Temperature Range
PoE	14°F~122°F (-10°C~50°C)

Connections

The Indoor IP Dome Camera uses Power over Ethernet (PoE) to power the camera. Make sure the power sourcing equipment (PSE) is in use in the network.

Connect one end of the PoE cable to the Ethernet port (RJ45) on the camera and the other end to the PSE hub or router.



Check the status of the network connection by looking at the link indicator and activity indicator LEDs. If the LEDs are not lit check your network connection. The green link LED indicates a network connection and the orange activity LED flashes to indicate network activity.

Connecting to the IP Camera

To access the camera setup menu, you need to run the Surveillix Device Search on your PC or recorder. To run the Surveillix Device Search application on your PC, insert the included software CD, or download the program from toshibasecurity.com, and follow the prompts.

1. Open **Device Search**, and click **Device Search**.
2. Locate your camera on the **Device Search** list.
3. To open the viewer software in your web browser, double-click the camera.

The first time you connect to the camera you will automatically prompted to install the ActiveX controller. If your internet browser doesn't install the viewer software, check the security settings or ActiveX controls and plug-in settings. If your internet browser asks for permission to install the ActiveX control, you must allow the ActiveX control to continue the installation.

To enable installation of ActiveX controls on Internet Explorer:

1. From the **Tools** menu, click **Internet Options**.
2. Click the **Security** tab and then click the **Internet** icon.
3. Click **Custom Level** and ensure that all **ActiveX controls and plug-ins** are set to **Enable** or **Prompt**.

To add the camera to your trusted sites:

1. From the **Tools** menu, click **Internet Options**.
2. Click the **Security** tab and then click the **Trusted Sites** icon.
3. Click **Sites**.
4. Type the **IP Address** of the camera. Ensure that the **Require server verification** check box is cleared.

For additional information on adjusting the settings of your internet browser contact technical support at 1-877-855-1349.

Default Username and Password

The username and password are case sensitive. It is strongly recommended that the password be changed after the initial setup to prevent unauthorized access.

Username – Admin

Password – 1234

Assigning an IP Address

Surveillix IP cameras come with the default IP address 192.168.0.250. To reset the IP address, use the Surveillix Device Search application to set a new static IP, or use DHCP.

1. Open the Device Search application.
2. Click **Device Search**, and then highlight your camera.
3. Right Click and click **Network Setup**.
4. Select **Static IP** and type the new IP address and other network information in the appropriate boxes.
- or -
Select **DHCP**.
5. Click **Apply**.
6. Click **OK** to acknowledge the change.
7. After one minute, click **Device Search** to search for all connected IP devices.
8. Double-click the camera.
9. Type the **Username** and **Password** to access the camera.

